

## DATA SHEET POPP CO-MELDER

(004407)

For its smart home products POPP trusts Z-Wave technology. Z-Wave is the international leading standard for wireless communication between intelligent devices in homes and offices and thereby the basis for successful home automation.



### Specifications:

- Integrated 10years lithium battery
- Alarm sound with 85dB/3m
- Easy-Press-Button for easy test and muting
- Memory function informs about previous CO detection
- Separate LED signal lights for power supply, alarm mode and error report
- Firmware update during use in field

Article Dimensions (WxHxL):	104 x 119 x 43 mm
Package Dimensions (WxHxL):	121 x 134 x 50 mm
Article net weight:	0.185 Kg
Article gross weight:	0.250 Kg
EAN:	0019962004407



## DATA SHEET POPP CO-MELDER

(004407)

Device Type:	Notification sensor (Sleeping Slave)
Actuator type:	electrochemical
Transmission protocol:	Z – Wave
Transmission frequency:	868.4 or 869.8 MHz EU
Z-Wave Plus:	yes
SmartStart:	no
Security:	SO
Repeater:	no
Beaming:	no
Firmware Version:	1.00
Z-Wave Version:	4.05
Transmission range:	uo to 30m
Certification-ID:	ZC10-16035025
Z-Wave Product-ID:	0x0154.0x0004.0x0003
Battery type:	ER14250 1/2 AA 3,6V (Z-Wave) CR124A 3,6V (Detector)
Battery life:	2 years(Z-Wave) 10 years (Detector)
IP Class:	IP20
Operating temperature:	0°C to 35°C
Humidity:	15 % to 95 %, no condensation
Storage temperature:	-10°C to 40°C
Norms:	BS EN 50270:2015, BS EN 60335-1:2012, BS EN 50291:2010